

모조지 80g / 184*260mm / 1도 양면 인쇄

中文如與英文有出入, 以英文為準! 版權CRG所有, 翻印必究!
圖有機會與實物不一樣, 品版更新規格, 將不另外通知!

中文如与英文有出入, 以英文为准! 版权CRG所有, 翻印必究!
图有机会与实物不一样, 品版更新规格, 将不另外通知!

Installation Manual
安裝指引 安裝指引

Door Thickness 90-100mm 門厚 內厚 90-100mm

室外 Outdoor
Door Thickness 90-100mm 門厚 內厚 90-100mm

Door 門門

Indoor 室內

Outdoor Body 室外鎖 室外鎖

Mortise 鎖體 鎖體

Indoor Plate 室內鎖底板 室內鎖底板

Indoor Body 室內鎖 室內鎖

Faceplate 面片

Striker 框片

Dust Box 防塵盒 防塵盒 90-100mm

50-60mm: Mortise shaft 89mm
70-100mm: Mortise shaft 160mm

PTMP4341ONTA REV.02

Screw List 線絲一覽 線絲一覽

For Metal Doors 鐵門 鐵門		For Wooden Doors 木門 木門	
A	(FH M5 X 10) 8EA Door Thickness 50-60mm] (BH M5 X 35) 4EA After tightening the mounting SHAFT JOIN.	A	(ST FH 4 X 30) 8EA Door Thickness 50-60mm] (BH M5 X 35) 4EA After tightening the mounting SHAFT JOIN.
B	70-80mm (BH M5 X 50) 4EA (SEM PH M4 X 12) 6EA	B	70-80mm (BH M5 X 50) 4EA (SEM PH M4 X 12) 6EA
C	(SEM PH M4 X 12) 6EA	C	(SEM PH M4 X 12) 6EA
D	(SD FH 4 X 20) 4EA	D	(SD FH 4 X 20) 4EA

⚠ Please note the screw specifications can be different depending on door material and thickness.
注意線絲尺寸會因應門物料及厚度而不同
注意線絲尺寸會因應門物料及厚度而不同

請查線絲尺寸
請查線絲尺寸
Please check the screw size.

Installation Manual 安裝指引 安裝指引

1. To Install Mortise
先安裝鎖體 先安裝鎖體

2. To Install Mortise Shaft
安裝鎖體芯 安裝鎖體芯

3. To Install Mortise Shaft Fixing Pin
安裝鎖體芯釘 安裝鎖體芯釘

4. To Install Outdoor Body
安裝室外鎖 安裝室外鎖

5. To Connect Cables
連接線 連接線

6. To Install Indoor Body
安裝室內鎖 安裝室內鎖

7. To Install Striker
安裝門框防塵盒及門框片(請對好位)
安裝門框防塵盒及門框片(請對好位)

The cable from outdoor unit needs to get through the hole on the mortise.
安裝室外鎖 安裝室外鎖

Please be careful not to make wire jamming problem.
請小心唔好壓到或弄破線
請小心唔好壓到或弄破線

Please install the strikers and dust box in the right direction, otherwise auto lock function will not work properly.

完成安裝後檢查清單
1) 請檢查自動鎖功能
2) 請檢查密碼, 咭及指紋登記及使用
3) 請檢查內部鎖定手柄是否合適
4) 請檢查9V後備緊急電源位可用
5) 請細讀使用手冊

完成安装后检查清单
1) 请检查自动锁功能
2) 请检查密码, 咭及指纹登记及使用
3) 请检查内部锁定手柄是否合适
4) 请检查9V后备紧急电源位可用
5) 请细读使用手册

Post - Installation Checklist
1. Please check the auto lock function.
2. Check password, RFID card and fingerprint registration & authentication.
3. Check inside force lock, if it is working properly.
4. Check emergency battery (9V) outlet.
5. Read carefully the user manual.

⚠ Check the type and thickness of the door for the installation.
If any extra panel has to be added, please make sure the door thickness states the original thickness plus the added thickness.
AFTER INSTALLATION INSERT BATTERIES WHILE DOOR IS OPEN.
請必落實門厚及門物料作正確安裝預備, 如加厚門, 請注意有機會有額外配件
安裝後請在打開門狀態下放入電池
請必先進門厚及門物料作正確安裝預備 如加厚門, 請注意有機會有額外配件
安裝後請在打開門狀態下放入電池